Weierstraß-Institut
für Angewandte Analysis und Stochastik
Leibniz-Institut im Forschungsverbund Berlin e. V.

Preprint ISSN 0946 – 8633

Spatio-temporal pulse propagation in nonlinear dispersive optical media

Carsten Brée, Shalva Amiranashvili, Uwe Bandelow

submitted: September 17, 2012

Weierstrass Institute
Mohrenstr. 39
10117 Berlin
Germany
E-Mail: carsten.bree@wias-berlin.de
shalva.amiranashvili@wias-berlin.de
uwe.bandelow@wias-berlin.de

No. 1733
Berlin 2012

2010 *Mathematics Subject Classification.* Primary 78A60, Secondary 35Q60, 35Q55.

2010 *Physics and Astronomy Classification Scheme.* 42.65.Re, 42.65.Sf, 42.65.Tg, 02.30.Mv, 52.35.Mw.

Key words and phrases. Ultrashort pulses, Nonlinear Schrödinger Equation, Filaments.

The work of Sh. Amiranashvili has been supported by the Deutsche Forschungsgemeinschaft (DFG) within the collaborative research center MATHEON under Grant D14.

Edited by
Weierstraß-Institut für Angewandte Analysis und Stochastik (WIAS)
Leibniz-Institut im Forschungsverbund Berlin e. V.
Mohrenstraße 39
10117 Berlin
Germany

Fax: +49 30 20372-303
E-Mail: preprint@wias-berlin.de
World Wide Web: http://www.wias-berlin.de/

Abstract

We discuss state-of-art approaches to modeling of propagation of ultrashort optical pulses in one and three spatial dimensions. We operate with the analytic signal formulation for the electric field rather than using the slowly varying envelope approximation, because the latter becomes questionable for few-cycle pulses. Suitable propagation models are naturally derived in terms of unidirectional approximation.

1 Introduction

The shortest events ever created by humans are ultrashort laser pulses with the current record being less then the Bohr-orbit time in hydrogen [1, 2]. These extreme pulses have dramatically triggered both fundamental and applied science. Their numerical treatment also created new challenges, since the phenomena in question involve many different time scales, such that a straightforward solution of the underlying field and material equations becomes impractical. On the other hand, one cannot eliminate the fastest time-scale of a single optical oscillation using the slowly varying envelope approximation (SVEA), because SVEA is no longer valid for ultrashort pulses. Therefore new models allowing for efficient numerical treatment have to be developed [3, 4, 5, 6]. We discuss several such models starting from a relatively simple case of a single-mode waveguide in which the field structure in the radial direction is fixed and only one propagation coordinate is involved [7, 8, 9, 10, 11]. Thereafter we turn to the full three-dimensional modeling of propagation of ultrashort pulses in gases [12, 13].

2 Scalar case

We start with an exemplary field-level numerical solution for an ultrashort pulse propagating in a single-mode fiber [8], Fig. 1. As one can see, the envelope structure is destroyed in the course of propagation. Another observation is that the pulse carrier frequency is gradually shifted and therefore not well defined. Such extreme propagation regimes require more careful treatment than the traditional envelope description. A natural approach is to take advantage of the nearly unidirectional character of pulse propagation.

In principle, an optical pulse in a single-mode waveguide can be described by a single field component $E(\vec{r},t)$ which, to a good approximation, is governed by a scalar wave equation

$$\vec{\nabla}^2 E - \frac{1}{c^2}\partial_t^2\left(\hat{\epsilon}E\right) = \mu_0 \partial_t^2 P_{\rm NL}, \tag{1}$$

where the dispersion operator $\hat{\epsilon}$ is defined in the frequency domain $\left(\hat{\epsilon}E\right)_\omega = \epsilon(\omega)E_\omega$ and $P_{\rm NL}$ denotes the nonlinear part of the induced polarization. For a given $\omega > 0$, the standard forward/backward solutions $E \sim e^{i(\pm\beta z - \omega t)}$ of the linearized Eq. (1) yield the propagation constant $\beta(\omega) = \omega n(\omega)/c$, where the refractive index $n(\omega) = \sqrt{\epsilon(\omega)}$.

We now relate $\beta(\omega)$ to the operator $\hat{\beta}$ such that

$$\left(\hat{\beta}E\right)_\omega = |\omega|\frac{n(\omega)}{c}E_\omega \qquad \text{and} \qquad \frac{1}{c^2}(i\partial_t)^2\hat{\epsilon} = \hat{\beta}^2,$$



Figure 1: Electric field (a) and spectrum (b) of the initial pulse. (c) and (d), the same after 10 ps of propagation in a bulk fluoride glass. The envelope structure of the initial pulse is gradually destroyed in the course of propagation. For further details see [8].

where $|\omega|$ is used to ensure that $\hat{\beta}$ transforms a real field into a real field [c.f., $\epsilon(-\omega) = \epsilon^*(\omega)$ and $\beta(-\omega) = -\beta^*(\omega)$]. In the following we also assume that the time-averaged pulse field vanishes, $\langle E \rangle = 0$, which is compatible to Eq. (1). For such pulses $E_\omega \to 0$ as $\omega \to 0$, and one can safely define $\hat{\beta}^{-1}E$. Using $\hat{\beta}$, Eq. (1) can be transformed to the form

$$\left(i\partial_z + \hat{\beta}\right)\left(i\partial_z - \hat{\beta}\right) E = \vec{\nabla}_\perp^2 E - \mu_0 \partial_t^2 P_{\mathrm{NL}}, \tag{2}$$

where $\vec{\nabla}_\perp^2 = \partial_x^2 + \partial_y^2$ is the transverse Laplace operator. At this point it is profitable:
(i) to decompose the real-valued electric field

$$E(\vec{r}, t) = \sum_\omega E_\omega(\vec{r}) e^{-i\omega t}, \qquad E_{-\omega} = E_\omega^*,$$

into the complex-valued negative- and positive-frequency parts

$$E = \sum_{\omega<0} E_\omega e^{-i\omega t} + \sum_{\omega>0} E_\omega e^{-i\omega t} = E^{(-)} + E^{(+)},$$

(ii) to introduce the analytic signal $\mathcal{E}$ for the electric field such that $E = \mathrm{Re}[\mathcal{E}]$

$$\mathcal{E}(\vec{r}, t) = 2E^{(+)}(\vec{r}, t) = 2\sum_{\omega>0} E_\omega(\vec{r}) e^{-i\omega t},$$

(iii) and to replace Eq. (2) with

$$\left(i\partial_z + \hat{\beta}\right)\left(i\partial_z - \hat{\beta}\right) \mathcal{E} = \vec{\nabla}_\perp^2 \mathcal{E} - 2\mu_0 \partial_t^2 P_{\mathrm{NL}}^{(+)}. \tag{3}$$

For a weakly nonlinear pulse consisting of forward waves propagating along the fiber we have $\left(i\partial_z - \hat{\beta}\right)\mathcal{E} \approx -2\hat{\beta}\mathcal{E}$ and therefore, neglecting the backward waves, one can simplify Eq. (3) to the form

$$\left(i\partial_z + \hat{\beta}\right)\mathcal{E} + \frac{\hat{\beta}^{-1}}{2}\vec{\nabla}_\perp^2 \mathcal{E} = \mu_0 \hat{\beta}^{-1} \partial_t^2 P_{\mathrm{NL}}^{(+)}.$$

For instance, neglecting the third harmonics generation in a cubic medium with $P_{\rm NL} = \epsilon_0\chi^{(3)}E^3$, one can approximate the positive frequency part of E^3 by $\frac{3}{8}\left(|\mathcal{E}|^2\mathcal{E}\right)^{(+)}$. The propagation equation

$$\left(i\partial_z + \hat{\beta}\right)\mathcal{E} + \frac{\hat{\beta}^{-1}}{2}\vec{\nabla}_\perp^2\mathcal{E} = \frac{3\chi^{(3)}}{8c^2}\hat{\beta}^{-1}\partial_t^2\left(|\mathcal{E}|^2\mathcal{E}\right)^{(+)} \tag{4}$$

looks then similar to the generalized nonlinear Schrödingier equation (NSE) and can be solved with the same numerical technique. However, Eq. (4) is completely independent on SVEA. If the pulse in question can be characterized by a narrow spectrum with the carrier frequency ω_0 and the corresponding wave vector $\beta_0 = \beta(\omega_0)$, then $\partial_t^2 \approx -\omega_0^2$, $\beta^{-1} \approx 1/\beta_0$, and

$$\left(i\partial_z + \hat{\beta}\right)\mathcal{E} + \frac{1}{2\beta_0}\vec{\nabla}_\perp^2\mathcal{E} + \frac{3\omega_0\chi^{(3)}}{8cn(\omega_0)}|\mathcal{E}|^2\mathcal{E} = 0,$$

where the latter equation can be related to the 1D NSE for the traditional pulse envelope $\psi(z,\tau)$ by a standard transformation to the pulse-comoving frame and projection onto the dominant waveguide mode [14]

$$\mathcal{E}(\vec{r},t) = \mathfrak{R}(x,y)\psi(z,\tau)e^{i(\beta_0 z - \omega_0 t)} + \text{h.o.t.},$$

where $\tau = t - \beta_1 z$ is the retarded time, $\beta_1 = \beta'(\omega_0)$ is the inverse group velocity, and $\mathfrak{R}(x,y)$ is the approximately fixed radial field structure. The same projection technique can be applied directly to Eq. (4), the result has the same basic structure

$$i\partial_z\mathcal{E}(z,t) + \hat{\beta}\mathcal{E}(z,t) = \frac{3\chi^{(3)}}{8c^2}\hat{\beta}^{-1}\partial_t^2\left(|\mathcal{E}|^2\mathcal{E}\right)^{(+)},$$

but attributes to the so-called effective dispersion $\beta_{\rm eff}(\omega)$ which depends on the fiber in question.

3 Vectorial case

In homogeneous media without (linear) waveguiding one has to account, in principle, for a fully vectorial description of the electric field $\vec{E}$, e.g., in the frequency domain by

$$[\vec{\nabla}^2 + \beta^2(\omega)]\vec{E}_\omega = \vec{S}_\omega. \tag{5}$$

The source term $\vec{S}_\omega$ is given by

$$\vec{S}_\omega = -\mu_0\omega^2\vec{P}_{\rm NL,\omega} + i\mu_0\omega\vec{J}_\omega + \frac{1}{\epsilon_0}\vec{\nabla}\left(\rho - \vec{\nabla}\cdot\vec{P}_\omega\right), \tag{6}$$

and takes account of the nonlinear part $\vec{P}_{\rm NL,\omega}$ of the total polarization density $\vec{P}_\omega$, the existence of free carriers with density ρ and current density $\vec{J}_\omega$, respectively. The last term on the r.h.s. of Eq. (6) models vectorial effects which become important for strongly divergent beams occuring under extreme focusing conditions. Scalar approximations can be restored for many experimental situations of interest. Nonlinear self-focusing effects may increase the optical intensity to trigger photoionization, which requires to include free carrier terms. Analogous to the previous